

8 kVA Honda Powered Petrol Generator with RCD & E-Start

8 kVA Honda Powered Electric Start Generator complete with all the extras suitable for work site usage. Featuring RCD protected outlets and sturdy frame. The RCD earth leakage protected outlets are Work Safe approved and comply with Australian Standards.

Specifications

Power Rating:	8 kVA
Alternator Rating:	8 kVA
Engine Model:	Honda GX390
Phase:	1 phase
Starting System:	Recoil/Electric
Fuel Tank Capacity:	6.1 L
Noise Level @ 7m:	72 dBA
Approx. Fuel Consumption @ 80% Load:	2.58 L/Hr
Operation Hours @ 80% Load:	2.36 hrs
Fuel Type:	Petrol
Volts:	230 V
Outlets:	2 x RCD Protected 15Amp, 1 x 32Amp Circuit Breaker
Dimensions:	780 x 570 x 570 mm
Weight:	95 kg



**Specifications are subject to change without notice*

OPTIONAL EXTRA P/N: 10-GN-N3-32MM-008

Attach the optional wheels & handles kit designed specifically for this model and turn it into the ultimate trade generator.



POWERED by
HONDA™

